



Custom made EL and LED Lighting

[www.wkled.nl](http://www.wkled.nl) / [www.wktrading.nl](http://www.wktrading.nl)

[wim@wkled.nl](mailto:wim@wkled.nl)

## WK LED DIMMER CV



### LED Intelligent Dim Switch

WK-3200 is an intelligent dim switch series dedicated to adjust the brightness of LED light, adopted the most advanced PWM (Pulse-Width Modulation) digital brightness-adjusting technology at present; Users can either turn around the knob manually or use the IR wireless remote control panel to control the brightness infinitely; Suitable for installation of commercial and household 86-style socket; can install the socket visibly outside the wall or inside the wall invisibly; can meet different brightness requirements at different time, and can extend life tenure of LED, so energy-saving, can adjust the brightness of both low-power and hi-power LED illumination lights.

### Features:

0-100% brightness adjust, infinite knob style dimming+ wireless IR remote dimming;  
256 grey scales, soft & smoothly, without flicker;  
PWM digital dimming + programs without current surge, longest life tenure of LED;  
25%-50%-75%-100% , 4 shortcuts of brightness options available;  
4 DIY modes, with Fluorescent Indicator & delay off button, users friendly;  
When load of constant current/voltage is beyond, add extra repeater to expand power;  
Several different options, convenient to control LED illumination with different circuits.

Part No.	<b>WK-3200-6A</b>
Input Power	DC12V/DC48V
Output Signal	Constant voltage PWM
Output Current	6A
Driving Qty	75/150/220/280W(12V/24V/36V/48V)
Grey Scale	256 levels
Switch Size	L87×W87(mm)
Remoter Size	L86×W33(mm)
Package Size	L96×W91×H61(mm)
G.W.	200G